CDMA MOBILE TELEPHONE

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a CDMA (Code Division Multiple Access) mobile communications system, and in

5   particular to a CDMA mobile telephone having a function of determining whether the CDMA mobile telephone is moving.

2. Description of the Related Art

There is a growing awareness of dangers that a driver takes a mobile telephone while driving a car or is surprised

10   with a sudden beep. To avoid such a dangerous situation, there have been proposed several mobile telephones having an automatic drive-mode setting function.

In Japanese Patent Application Unexamined Publication No. 11-234756, for example, a mobile telephone is provided with a

15   received signal level detector and a fading decision section, which are used to detect a period of fading occurrence. When the detected fading period is smaller than a predetermined time period, a controller determines that the mobile telephone is on the move and sets the mobile telephone to an automatic

20   answering mode in which, when an incoming call occurs, a response message is automatically sent to the caller without starting a ringer.

In the field of CDMA mobile communications, there has been disclosed a velocity detecting method using a Doppler frequency calculated based on variations in received signal level or widened frequency band due to fading (see Japanese Patent

5   Application Unexamined Publication No. 11-98071). To calculate the Doppler frequency, a CDMA mobile terminal is provided with a circuit for counting the number of times a received signal level has changed across an average level or a circuit for measuring the amount of widened frequency band.

10   However, a conventional mobile station needs an extra circuit for detecting fading occurrence, variations in received signal level, or the amount of widened frequency band, resulting in increased amount of hardware.

SUMMARY OF THE INVENTION

15   An object of the present invention is to provide a CDMA mobile telephone allowing the drive mode to be automatically set and canceled without increasing the amount of hardware.

According to the present invention, a mobile telephone apparatus operable in a CDMA communications system includes:

20   a despreading circuit for despreading received spectrum-spread data of a plurality of branches to produce despread data each corresponding a plurality of fingers; a frequency offset detector for detecting a frequency offset for each of the fingers

from the despread data; a movement determiner for determining whether the mobile telephone is moving at speeds higher than a predetermined speed, based on frequency offsets received from the frequency offset detector: and a mode controller for

5   switching an operation mode between a drive mode and a normal mode depending on whether the mobile telephone apparatus is moving at speeds higher than the predetermined speed.

The movement determiner may include a Doppler frequency calculator for calculating Doppler frequencies for respective

10   ones of the branches by combining the frequency offsets for respective ones of the fingers; a first determiner for determining whether there is a pair of Doppler frequencies satisfying a first condition such that the Doppler frequencies are of opposite sign; a second determiner for determining whether

15   the Doppler frequencies satisfy a second condition such that an absolute value of each of the Doppler frequencies is not smaller than a first reference value; and a determination controller for determining that the mobile telephone apparatus is moving at speeds higher than the predetermined speed when

20   a pair of Doppler frequencies satisfying the first and second conditions exists.

The determination controller may output a first interrupt signal to the mode controller when the pair of Doppler frequencies satisfying the first and second conditions exist

25   and outputs a second interrupt signal to the mode controller when a pair of Doppler frequencies satisfying the first and

second conditions does not exist, wherein the mode controller
sets the mobile telephone apparatus to the drive mode when
receiving the first interrupt signal and sets the mobile
telephone apparatus to the normal mode when receiving the second

5   interrupt signal.

The movement determiner may include: a branch frequency
offset calculator for calculating branch frequency offsets for
respective ones of the branches by combining the frequency
offsets for respective ones of the fingers; a first determiner

10   for determining whether there is a branch frequency offset
satisfying a first condition such that an absolute value of the
branch frequency offset is greater than a second reference value;
a second determiner for determining whether there is at least
one branch frequency offset satisfying a second condition such

15   that an absolute value of the branch frequency offset is not
greater than a maximum correction threshold of AFC (automatic
frequency control) operation performed in the mobile telephone
apparatus; and a determination controller for determining that
the mobile telephone apparatus is moving at speeds higher than

20   the predetermined speed when there are both the branch frequency
offset satisfying the first condition and the at least one branch
frequency offset satisfying the second condition.

The determination controller may output a first interrupt
signal to the mode controller when there are both the branch

25   frequency offset satisfying the first condition and the at least
one branch frequency offset satisfying the second condition,

and outputs a second interrupt signal to the mode controller when there is neither the branch frequency offset satisfying the first condition nor the at least one branch frequency offset satisfying the second condition, wherein the mode controller

5   sets the mobile telephone apparatus to the drive mode when receiving the first interrupt signal and sets the mobile telephone apparatus to the normal mode when receiving the second interrupt signal.

The mobile telephone apparatus may further include a

10   display controller for controlling a display device when the mobile telephone apparatus is moving at speeds higher than the predetermined speed such that a message indicating that the mobile telephone apparatus is moving at speeds higher than the predetermined speed is displayed on the display device.

15   The mobile telephone apparatus may further include: a voice message generator for generating a predetermined voice message when an incoming call occurs during the drive mode; and a communication controller for transmitting the predetermined voice message to a caller.

20   The mobile telephone apparatus may further include: a communication controller for transmitting a network system a drive-mode message indicating that the mobile telephone apparatus is moving at speeds higher than the predetermined speed, when the operation mode has been changed to the drive mode,

25   wherein the network system has a voice message system in which, when an incoming call occurs after having received the drive-mode

message from the mobile telephone apparatus, the voice message
system transmits a predetermined voice message to a caller.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a CDMA mobile telephone

5   according to a first embodiment of the present invention;

FIG. 2 is a flow chart showing a movement decision method
according to the first embodiment of the present invention;

FIG. 3 is a flow chart showing a drive-mode switch
operation in the first embodiment;

10   FIG. 4 is a schematic diagram showing an example of a CDMA
cellular system for explanation of a fundamental operation of
the present invention;

FIG. 5 is a block diagram showing a CDMA mobile telephone
according to a second embodiment of the present invention;

15   FIG. 6 is a flow chart showing a movement decision method
according to the second embodiment of the present invention;
and

FIG. 7 is a flow chart showing a drive-mode switch
operation in the second embodiment.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring to Fig. 1, a CDMA mobile telephone includes a
5   heterodyne radio transceiver. A radio-frequency (RF) signal
received at an antenna 1 is amplified by a low-noise amplifier
2 and then is down-converted from RF to intermediate frequency
(IF) by a down converter 3 using a first local signal LO1. The
IF received signal is amplified by a variable-gain amplifier
10   4 depending on an automatic gain control signal so that the input
level at an analog-to-digital converter 6 is kept constant. The
IF received signal is output to a quadrature demodulator (DEM)
5, which uses a second local signal LO2 to demodulate the IF
received signal to produce an analog baseband signal. The
15   analog baseband signal is converted by the analog-to-digital
converter 6 into a digital baseband signal.

The first and second local signals LO1 and LO2 are
generated by a phase-locked loop circuit 7 receiving a reference
oscillation signal from a reference oscillator (here, TCXO) 8.
20   The reference oscillator 8 is a voltage-controlled oscillator
having a control terminal connected to the output of an
accumulator 9 (which will be described later).

The digital baseband signal is output from the

analog-to-digital converter 6 to both a finger circuit 10 and

a delay-profile searcher 12. The finger circuit 10 is a

RAKE-finger circuit composed of a predetermined number of

fingers each including correlators. Each of the fingers in the

5   finger circuit 10 produces despread data from the digital

baseband signal based on a frame timing signal received from

a timing generator 14. The respective despread data of the

finger are output to a frequency offset estimator 11 and a RAKE

circuit 15.

10   The delay-profile searcher 12 produces delay-profile

data and an amount of frame-timing correction from the digital

baseband signal based on a frame timing signal received from

the timing generator 14. The frame-timing correction amount is

output to the timing generator 14. The timing generator 14

15   generates an ideal frame timing signal based on the reference

oscillation signal received from the reference oscillator 8 and

then produces the frame timing signal by adding the frame-timing

correction amount received from the delay-profile searcher 12

to the ideal frame timing signal. The frame timing signal is

20   supplied to the finger circuit 10 and the delay-profile searcher

12. Then, the-profile searcher 12 produces an updated amount

of frame-timing correction based on the frame timing signal

received from the timing generator 14 and outputs the updated

frame-timing correction amount to the timing generator 14. In

25   this manner, the timing generator 14 can supply a precise frame

timing signal to the finger circuit 10 and the delay-profile

searcher 12 at all times.

The frequency offset estimator 11 calculates a frequency

offset for each finger by using known data such as pilot data

included in the despread data received from the finger circuit

5   10. The calculated frequency offset for each finger is output

to the RAKE circuit 15 and a high-speed-movement decision section

16. Further, the frequency offset estimator 11 combines the

frequency offsets that are weighted taking into account an

electric field level and signal-to-noise ratio of a received

10   signal to produce a combined frequency offset, which is output

to the accumulator 9. The accumulator 9 adds the combined

frequency offset to a current frequency offset to output a

frequency control voltage to the reference oscillator 8. In

this way, the AFC (Automatic Frequency Control) operation is

15   performed.

The high-speed-movement decision section 16 uses the

calculated frequency offset for each finger to determine whether

the mobile telephone is moving at high speeds. The high-

speed-movement decision section 16 generates an interrupt

20   signal to a micro processor (CPU) 13 so as to notify it whether

the mobile telephone is moving at high speeds. The details will

be described later by referring to Fig. 2.

The RAKE circuit 15 weights the despread data received

from the finger circuit 10 taking into account an electric field

25   level and signal-to-noise ratio of a received signal and combines

the weighted despread data to produce demodulated data. The

demodulated data is output to a speech DSP (digital signal

processor) 17, which performs coding/decoding according to a

predetermined codec algorithm such as G729. The decoded data

is output to a codec 18, which produces an analog voice signal

5   from the decoded data to drive a speaker 19.

On the other hand, an analog voice signal inputted by a

microphone 20 is converted to a digital voice signal by the codec

18 and then the digital voice signal is encoded by the speech

codec 17. The encoded data is output to a channel codec 23, which

10   performs error-correcting coding and channel control of the

encoded data to produce transmission data. The transmission

data is converted by a digital-to-analog converter 24 to an

analog transmission baseband signal. A modulator 25 modulates

the second local oscillation signal LO2 according to the analog

15   transmission baseband signal to produce an IF-band transmission

signal. After the IF-band transmission signal is amplified by

a variable-gain amplifier 26, it is up-converted by an up

converter 27 using the first local oscillation signal LO1 into

transmission radio frequency. The transmission RF signal is

20   amplified by a power amplifier 28 before transmitted through

the antenna 1.

The mobile telephone is further provided with a liquid

crystal display (LCD) device 22, which is driven by a LCD driver

21 under control of the CPU 13.

25   Referring to Fig. 2, the high-speed-movement decision

section 16 inputs N frequency offsets $\Delta f_1 - \Delta f_N$ each corresponding

to N fingers from the frequency offset estimator 11 (step S101).

Thereafter, the high-speed-movement decision section 16

calculates Doppler frequencies Df_1-Df_M for respective ones of

the receiving branches by combining the frequency offsets Δ

5 f_1-Δf_N which are weighted for respective ones of receiving

branches taking into account an electric field level, a

signal-to-noise ratio and the like of a received signal (step

S102).

  Subsequently, it is determined whether there is a pair

10 of Doppler frequencies (Df_i, Df_j) satisfying $Df_i \times Df_j < 0$ (step

S103). In other words, the high-speed-movement decision

section 16 searches the Doppler frequencies Df_1-Df_M for a pair

of Doppler frequencies (Df_i, Df_j) satisfying that Df_i and Df_j are

of opposite sign.

15 When such a pair of Doppler frequencies (Df_i, Df_j) is found

(YES at step S103), it is further determined whether the absolute

values $|Df_i|$ and $|Df_j|$ are equal to or greater than a predetermined

reference set value f_{REF1} (step S104). If the absolute values

$|Df_i|$ and $|Df_j|$ are not smaller than the predetermined reference

20 set value f_{REF1} (YES at step S104), then the high-speed-movement

decision section 16 generates an interrupt signal IS_H to the CPU

13 to indicate that the mobile telephone is on the move (step

S105).

  If there is no pair of Doppler frequencies (Df_i, Df_j)

25 satisfying $Df_i \times Df_j < 0$ (NO at step S103) or if at least one

of the absolute values $|Df_i|$ and $|Df_j|$ is smaller than the

predetermined reference set value f_{REF1} (NO at step S104), then

the high-speed-movement decision section 16 generates an

interrupt signal IS_L to the CPU 13 to indicate that the mobile

telephone stops or does not move at high speeds (step S106).

5   Referring to Fig. 3, the CPU 13 in standby status

determines whether an interrupt occurs (step S201). When the

interrupt signal IS_H is generated (YES at step S201), the CPU

13 controls the LCD driver 21 so that a message "on high-speed

move" is displayed on the LCD 22 (step S202). Such a message

10   makes the driver aware of setting the mobile telephone to the

drive mode in which the ringer is not started but an automatic

answering function when an incoming call occurs.

The CPU 13 determines whether an incoming call occurs on

the move (step S203). If an incoming call occurs on the move

15   (YES at step S203), the CPU 13 does not make a beep but reads

preset voice guidance data from a memory (not shown) and

instructs the speech DSP 17 to transmit it to the transmission

system (step S204). Accordingly, the preset voice guidance

message, for example, "now driving a car", is automatically

20   transmitted to the caller. The CPU 13 sets the mobile telephone

to a standby mode by repeatedly performing the steps S203-S204

until the interrupt signal IS_L is generated (NO at step S205).

When the interrupt signal IS_L is generated (YES at step

S205), the CPU 13 stops displaying "On high speed move" on the

25   LCD 22 and cancels the preset voice guidance transmission (step

S206). In other words, when the mobile telephone does not move

at high speeds, the drive mode is automatically canceled. In this manner, the drive mode is automatically set and reset depending on the interrupt signal generated by the high-speed-movement decision section 16 without driver's attention

5   to the mobile telephone. The high-speed-movement decision section 16 is allowed to be turn on and off depending on a user's instruction through a keypad (not shown).

Referring to Fig. 4, it is assumed for simplicity that three base transceiver stations 301-303 forms service areas

10   SA1-SA3 which are in part overlapped with each other and further that a mobile station MS is moving toward the base transceiver station 303 as indicated by an arrow at a constant velocity 100Km/h while receiving three branches corresponding to the base transceiver stations 301-303.

15   Assuming that the carrier frequency is 2GHz, the Doppler frequency Df_1 for the base transceiver station 301 is about -185 Hz, Df_3 for the base transceiver station 303 is about +185 Hz, and Df_2 for the base transceiver station 302 is almost 0 Hz. In this case, when the predetermined reference set value f_{REF1} is

20   previously set to 100Hz, the first condition ($Df_1 \times Df_3 < 0$) and the second condition ($|Df_1| = |Df_3| = 185$ is greater than f_{REF1} = 100) are both satisfied. Accordingly, the high-speed-movement decision section 16 generates the interrupt signal IS_H to the CPU 13 and thereby the message indicating that the mobile

25   telephone is on the move is displayed on the LCD 22. Such a message makes the driver aware of setting the mobile telephone

to the drive mode. Therefore, when an incoming call occurs on driving, the automatic answering function is automatically set to send the preset voice guidance to the caller.

When the velocity of the mobile telephone is reduced to some extent without changing in direction, $|Df_1|$ and $|Df_3|$ become smaller than $f_{REF1} = 100$ and therefore the interrupt signal IS_L is generated (YES at step S205). At this time, the message indicating that the mobile telephone is on the move disappears on the LCD 22 and the automatic answering function becomes inactive. That is, the drive mode is automatically canceled.

The high-speed-movement decision section 16 may be implemented with software. In other words, the above-described high-speed-movement decision can be realized by only adding a high-speed-movement decision program to the existing control program to run on the CPU 13. Accordingly, the drive mode can be automatically switched on and off without increasing the amount of hardware.

Referring to Fig. 5, a second embodiment of the mobile telephone has a function of notifying the network that the mobile telephone is moving at high speeds. Such a notification is performed by the CPU 13 controlling a transmission system 30 including the channel codec 23. When an incoming call occurs after receiving such a notification from the mobile telephone, the network does not call the mobile telephone but sends a preset voice message indicating that the destination terminal is moving at high speeds to the caller. In Fig. 5, circuit blocks similar

to those previously described with reference to Fig. 1 are

denoted by the same reference numerals and the descriptions are

omitted. Hereafter, the high-speed-movement decision method

will be described in detail.

5   Referring to Fig. 6, the high-speed-movement decision

section 16 inputs N frequency offsets $\Delta f_1 - \Delta f_N$ each corresponding

to N fingers from the frequency offset estimator 11 (step S401).

Thereafter, the high-speed-movement decision section 16

calculates branch frequency offsets $\Delta Bf_1 - \Delta Bf_M$ for respective

10   ones of the receiving branches by combining the frequency offsets

$\Delta f_1 - \Delta f_N$ which are weighted for respective ones of receiving

branches taking into account an electric field level, a

signal-to-noise ratio and the like of a received signal (step

S402).

15   Subsequently, it is determined whether there is a branch

frequency offset Bf_i satisfying that the absolute value of Δ

Bf_i is greater than a predetermined reference set value f_{REF2},

that is, $|\Delta Bf_i| > f_{REF2}$ (step S403).

When such a branch frequency offset ΔBf_i is found (YES

20   at step S403), it is further determined whether there is at least

one branch frequency offset ΔBf_j satisfying that the absolute

value of ΔBf_j is equal to or smaller than the maximum AFC

correction threshold L_{AFC}, that is, $|\Delta Bf_i|$ L_{AFC} (step S404). If

at least one branch frequency offset ΔBf_j satisfying the

25   condition is found (YES at step S404), then the high-speed-

movement decision section 16 generates an interrupt signal IS_H

to the CPU 13 to indicate that the mobile telephone is on the
move (step S405).

If no branch frequency offset Bf_i satisfying $|\Delta Bf_i| > f_{NET3}$
is found (NO at step S403) or if no branch frequency offset Δ

5   Bf_j satisfying $|\Delta Bf_i|$ L_{Arc} is found (NO at step S404), then the
high-speed-movement decision section 16 generates an interrupt
signal IS_L to the CPU 13 to indicate that the mobile telephone
stops or does not move at high speeds (step S406).

Referring to Fig. 7, the CPU 13 in standby status

10   determines whether an interrupt occurs (step S501). When the
high-speed-movement interrupt signal IS_H is generated (YES at
step S501), the CPU 13 controls the transmission system 30 such
that a message indicating that the mobile telephone is moving
at high speeds is transmitted to the network (step S502). Such

15   a message may be displayed on the LCD 22 to make the driver aware
of setting the mobile telephone to the drive mode. Thereafter,
the CPU 13 returns to the standby status (step S503) and sets
the mobile telephone to the standby mode until the not-movement
interrupt signal IS_L is generated (NO at step S504).

20   When the interrupt signal IS_L is generated (YES at step
S504), the CPU 13 controls the transmission system 30 such that
a message indicating that the mobile telephone does not move
at high speeds is transmitted to the network (step S505). Such
a message may be displayed on the LCD 22 to make the driver aware

25   of resetting the drive mode. Thereafter, control goes back to
the step S501.

In the case where an incoming call to the mobile telephone
occurs after receiving the high-speed-movement notification
from the mobile telephone, the network starts a voice mail system
to send the caller a preset voice message indicating that the

5   destination terminal is moving at high speeds. When receiving
the not-movement notification from the mobile telephone, the
network resets the voice mail system and returns to the normal
call processing operation. Since the automatic answering
function is provided in the network side in the second embodiment,

10   the amount of hardware in the mobile telephone is further
reduced.

In this manner, the drive mode is automatically set and
canceled depending on an interrupt signal generated by the
high-speed-movement decision section 16 without driver's

15   attention to the mobile telephone. The high-speed-movement
decision section 16 is allowed to be turn on and off depending
on a user's instruction through a keypad (not shown).

In the above-described case as shown in Fig. 4, it is
assumed that the base transceiver station 303 is selected as

20   a main branch and the AFC operation is performed by weighting
the main branch at a rate of approximately 100%. In this case,
the branch frequency offset ΔBf_3 for the base transceiver station
303 is almost 0Hz and the branch frequency offset ΔBf_1 for the
base transceiver station 301 is almost -370Hz. Therefore, in

25   the case of the predetermined reference set value f_{REF2} being set
to 300Hz, $|\Delta Bf_1| > f_{REF2}$ (YES at step S403) and $|\Delta Bf_3| < L_{AFC}$ (YES

at step S404). Since both conditions are satisfied, the
high-speed-movement decision section 16 generates an interrupt
signal IS_H to the CPU 13 to indicate that the mobile telephone
is on the move (step S405).

5   When the high-speed-movement interrupt signal IS_H is
generated, the CPU 13 set the mobile telephone to the drive mode
and the notification indicating that the mobile telephone is
moving at high speeds is transmitted to the network. In this
status, when an incoming call occurs, the network sends a voice

10   message having the same contents to the caller.

On the other hand, when the velocity of the mobile
telephone is reduced to some extent without changing in direction,
$|\Delta Bf_1|$ become smaller than $f_{REF2} = 300$ and therefore the interrupt
signal IS_L is generated, resulting in the drive mode being

15   automatically canceled.

As described above, when the user is driving a car and
moving at high speeds, the mobile telephone is automatically
set to the drive mode. When the user stops the car or reduces
speed to below a predetermined velocity, the mobile telephone

20   is automatically reset to the normal operation mode. Since a
preset message is displayed on the LCD, the user is aware of
setting the mobile telephone to the drive mode. Further, when
an incoming call occurs on driving, a preset voice message is
automatically sent from the network to the caller. Therefore,

25   the caller is aware of the destination telephone moving at high
speeds.

FQ5-503

The high-speed-movement decision method as shown in Fig.
2 may be combined with the operation of the CPU 13 as shown in
Fig. 7. Contrarily, the high-speed-movement decision method as
shown in Fig. 6 may be combined with the operation of the CPU
5   13 as shown in Fig. 3.